Mohamed K. Shahin, Alaa Tharwat, Tarek Gaber* and Aboul Ella Hassanien

A Wheelchair Control System Using Human-Machine Interaction: Single-Modal and Multimodal Approaches

DOI 10.1515/jisys-2017-0085

Received October 19, 2016; previously published online June 12, 2017.

Abstract: Recent research studies showed that brain-controlled systems/devices are breakthrough technology. Such devices can provide disabled people with the power to control the movement of the wheelchair using different signals (e.g. EEG signals, head movements, and facial expressions). With this technology, disabled people can remotely steer a wheelchair, a computer, or a tablet. This paper introduces a simple, low-cost human-machine interface system to help chaired people to control their wheelchair using several control sources. To achieve this paper's aim, a laptop was installed on a wheelchair in front of the sitting person, and the 14-electrode Emotiv EPOC headset was used to collect the person's head impressions from the skull surface. The superficially picked-up signals, containing the brain thoughts, head gestures, and facial emotions, were electrically encoded and then wirelessly sent to a personal computer to be interpreted and then translated into useful control instructions. Using these signals, two wheelchair control modes were proposed: automatic (using single-modal and multimodal approaches) and manual control. The automatic mode controller was accomplished using a software controller (Arduino), whereas a simple hardware controller was used for the manual mode. The proposed solution was designed using wheelchair, Emotiv EPOC EEG headset, Arduino microcontroller, and Processing language. It was then tested by totally chaired volunteers under different levels of trajectories. The results showed that the person's thoughts can be used to seamlessly control his/her wheelchair and the proposed system can be configured to suit many levels and degrees of disability.

Keywords: Brain-computer interface (BCI), control, EEG signals, facial expressions, head movements, multimodal, single modal, wheelchair.

1 Introduction

Many people could unexpectedly get injured during different events, including falls, accidents, violence, or even injuries during sports practicing. These events may lead to devastating neuromuscular disorders, causing severe disabilities due to spinal cord injuries. Because of the lack of the nerve supply, every injured part of the human body will be paralyzed (e.g. causing chaired people) [18, 19]. Thus, there is an emerging need to provide help for these people to elevate their capabilities to practice their daily life routines by them-

^{*}Corresponding author: Tarek Gaber, Scientific Research Group in Egypt (SRGE), Cairo, Egypt; and Faculty of Computers and Informatics, Suez Canal University, Ismailia, Ismailia Governorate, Egypt, e-mail: tmgaber@gmail.com. https://orcid.org/0000-0003-4065-4191

Mohamed K. Shahin: Faculty of Engineering, Suez Canal University, Ismailia, Ismailia Governorate, Egypt

Alaa Tharwat: Faculty of Engineering, Suez Canal University, Ismailia, Ismailia Governorate, Egypt; Faculty of Computer Science and Engineering, Frankfurt University of Applied Sciences, Frankfurt am Main, Germany; and Scientific Research Group in Egypt (SRGE), Cairo, Egypt

Aboul Ella Hassanien: Faculty of Computers and Information, Cairo University, Al Doqi, Giza Governorate, Egypt; and Scientific Research Group in Egypt (SRGE), Cairo, Egypt

selves without others' assistance. The ability to move is considered of highest priority for chaired people, and this ability could be realized using an electric-powered wheelchair (EPW).

The wheelchair can be controlled either manually (using joysticks, mouse, or keypad) or automatically (using head movements, eye tracking, or tongue). Most of the manual designs need the seated person to be able to precisely control the wheelchair movements by hand or fingers [11, 15, 17]. In cases including the absence of the nerve supply from their brains to their motor muscles and limbs, many disabled persons could not fulfill the traditional joystick control requirements [16]. For example, in the case of a spinal cord-neck region injury, there is no nerve supply from the brain down to any of the limbs. In such cases, the automatically generated signals from the victim's head itself to provide self-mobility cannot control the traditional joysticks [1, 40].

Automatic models were designed relying on a source of information that the disabled person can generate and repeat, for example, head gestures [22, 56], tongue motion [26], and eye iris position tracking and detection [55]. Gajwani and Chhabria implemented an eye tracking system to control the wheelchair movement using a USB camera mounted in front of the sitting user's eve [20]. Their model tracks the eve movements toward the left or right direction to control the wheelchair. Also, in this model, the eye blinking feature was used to control the starting and stopping of the wheelchair. In another research [35], a video chargecoupled device (CCD) camera and a frame grabber were used to analyze a series of human pupil images to track the eye movements of the user to control the wheelchair. The eye movement was detected by recording the standing cornea-retina potential that resulted from hyperpolarizations and depolarizations existing between the cornea and the retina. Jia et al. used a camera to track the nose of the user's face as a measure for the head position and orientation (i.e. head movement) to control the wheelchair movement [22]. Bergasa et al. proposed a model that uses head movements to control the wheelchair for handicapped people with severe disabilities [7]. In another research, Bergasa et al. used a 2D color face tracker and a fuzzy detector to detect the face movements of the user and then generate some commands to drive the wheelchair [8]. Kuno et al. proposed a robotic wheelchair using the face direction to convey the user's attention [34]. Their proposed system used the face direction to move the wheelchair in that direction, which is a natural action. In the state of th chair [30]. Facial expressions were used to generate commands to control the movements of the wheelchair. Faria et al. captured the facial expressions using a digital camera, and the collected images are preprocessed and interpreted by an application running on a laptop computer on the wheelchair [14]. Recently, Bastos-Filho et al. used eye blinks, eye movements, and head movements to generate a command, which is sent to a robotic wheelchair [5]. However, the performances of these camera-based systems are likely affected by environmental noises, such as illumination, brightness, and the camera position. Furthermore, eye tracking may lead to user fatigue and may affect the vision of the user in the long run [20, 42]. Also, Njah and Jallouli proposed a control method for wheelchair to provide automatic indoor navigation [39]. This method made use of two fuzzy controllers to ensure obstacle avoidance and an extended Kalman filter to achieve precise measurements.

Electromyography (EMG) signals from certain body movements (e.g. shoulder) can also be used to automatically control a wheelchair movement [29]. In Ref. [23], four EMG electrodes were attached to the sternocleidomastoid muscle, and the sensed signals were used to detect shoulder movements. In this work, the wheelchair can move forward when both shoulders move up. It can also move to the right or left when the shoulder either moves up right or left, respectively. Also, in Ref. [38], only two superficial EMG electrodes were used to detect shoulder movements to finally control a wheelchair. In addition, Xu et al. suggested a system to control a wheelchair using EMG signals generated by the facial movements [57]. Nonetheless, facial and shoulder muscles, used in Refs. [23, 38, 57], are weak and cannot be used for a long period [26].

Electroencephalography (EEG) signals also were used to control a wheelchair movement [47, 54]. Rebsamen et al. proposed a brain-controlled wheelchair that can navigate inside a typical hospital or office environment [41]. In another research, Lin et al. proposed a system that consists of a simple unipolar electrode to collect EEG signals and eye blinking to build a brain-computer interface (BCI) electric wheelchair [36]. A novel paradigm was proposed by Huang et al. [25]. This paradigm was based on the multiclass discrimination

of the spatiotemporally distinguishable phenomenon of event-related desynchronization/synchronization (ERD/ERS) in EEG signals, which are generated from the movements of the right/left hand. However, due to the low signal-to-noise ratio (SNR), the EEG signals, which are generated by the synchronous activity of millions of cortical neurons, are insufficient to decode accuracy [25].

The automatic wheelchair control could be achieved by exploiting the tongue and a set of Hall-effect sensors. Huo and Ghovanloo tried to alleviate the suffering of the disabled people using a tongue drive system [26]. By installing a small magnet piercing at the tongue tip, the chaired person can control the switching state of four to six magnetic sensors arranged externally on both face sides. Moreover, as the nerve supply of the tongue is directly connected to the brain and does not pass through the spinal cord, the proposed tongue control system has the main advantage of being completely voluntary for severe quadriplegic disability cases. However, as the user should receive a tongue piercing embedded with the magnetic tracer, this technique is considered a little invasive for long-term usage [13, 27, 31, 48].

Data/information fusion is the process of combining multiple data and knowledge representing the same real-world object into an accurate, consistent, and useful representation. The aim of the data fusion technique is to combine relevant information from two or more different data sources into a single one that gives a more precise description than any of the individual data sources [33, 51]. This technique was used in many machine learning applications such as classifier fusion [51], feature fusion [44], rank fusion/aggregation [46], and score fusion [50]. Moreover, the data fusion technique was used to combine two or more biometrics; this is called multimodal biometrics such as face + fingerprint [43], hand vein + hand geometry + fingerprint [45], or ear + finger knuckle [49]. Multimodal biometrics was used (1) to improve the performance of the biometric system that may not be possible using one of a single biometrics, (2) to solve the problem of noisy sensor data, and (3) for the nonuniversality of the biometric trait [43]. In addition, head pose and eye location were used for gaze estimation [53].

In this paper, simple and severe inability scenarios for chaired people were considered. These people may or may not be able to (1) manually control joysticks, (2) move their shoulders and bodies for a long time, (3) use models that are degraded with the background speaker noise as voice recognition-based models, (4) use models that are affected by the involuntary component of the eye movements and blinking in eye tracking systems, and (5) use models that are affected by environmental noises such as illumination, brightness, and the camera position. At the same time, they need a relatively accurate controllable wheelchair. Hence, different alternative criteria such as EEG signals and facial expressions must be used to meet their needs.

In this work, an automatic control model was proposed to allow chaired people to seamlessly control their wheelchairs. This model has two control modes: automatic and manual. In the automatic mode, the wheelchair is controlled using signals, which are generated automatically. This will be achieved using the signals generated from facial expressions, head movements, and superficial EEG signals. The wheelchair was steered using a software controlling module via one or a combination of the acquired signals (i.e. single-modal or multimodal control). In the manual mode, the chair was controlled using a simple hardware controller with a keypad designed from four push button switches.

The rest of the paper is organized as follows. Section 2 introduces some theoretical background about the proposed model. Section 3 demonstrates the proposed prototype realization, including a brief description of the proposed model (i.e. control of a battery-powered wheelchair). Further, two modes for controlling the wheelchair, automatic and manual control modes, are briefly explained. The experimental results, evaluation, and discussions are given in Section 4 to show the feasibility and performance of the two control modes of the proposed HMI system in the real operating settings. Finally, Section 5 concludes this paper.

2 Preliminary

This section gives overviews of the devices, tools, and techniques that are used in the proposed model.

2.1 Emotiv EPOC EEG Headset

EEG is an electrophysiological monitoring method to detect and record the electrical activities of the brain. These activities are represented by voltage fluctuation that results from ionic current within the neurons of the brain, and it is measured by EEG. The Emotiv EPOC EEG headset was used to collect EEG signals. This headset consists of 14 electrodes, which are located on the surface of the scalp (see Figure 1). The EPOC is produced by a company called Emotiv[®], which specializes in producing a BCI system and its associated software [52]. The EPOC has three main software modules: (1) Cognitive suite: to detect thoughts and thinkings, (2) Expressive suite: for facial expression recognition, and (3) Affective suite: to interpret emotions [25, 52]. Moreover, the EPOC headset encapsulates a gyroscope to detect head movements and orientation. The main advantages of the EPOC sensor are (1) high reliability of the output signals, (2) lightweight, (3) ease of installation, (4) wireless transmission ability to any personal computer (PC) via Bluetooth connectivity, and (5) containing a long-life rechargeable battery. In this research, the EPOC was used to read, analyze, and process the user's brainwaves, which were then used to control the wheelchair using the Arduino microcontroller.

The Emotiv EPOC headset was used in many systems to implement smart human-computer interaction systems [10, 21, 42]. For example, Gomez-Gil et al. used the EPOC headset to recognize four types of muscular events: (1) eyes looking to the right while jaw opened, (2) eyes looking to the right while jaw closed, (3) eyes looking to the left while jaw opened, and (4) eyes looking to the left while jaw closed. They used these muscular events to steer an agricultural tractor. In [9, 10], EPOC was used to develop a system called Virtual Move to navigate through Google Street View (GSV). Their proposed system exploited the EPOC capabilities to detect head movements, facial expressions, thoughts, and emotional states. Using two control modes, one



Figure 1: Emotiv EPOC Headset that was used to Control the Intelligent Wheelchair Setup for Assisting the Locked-In Subjects.

with single head movement and the second with four head movements, Rechy-Ramirez et al. implemented a human-machine interface (HMI) for hands-free control of an EPW [42].

In our model, EPOC was used to collect facial expressions, head movements, and EEG signals. The signals were sent to the PC wirelessly. The Emotiv EPOC Software Development Kit (SDK) was used to interpret the received signals to take suitable actions according to these signals.

2.2 Arduino Microcontroller

The Arduino is a microcontroller with an open-source platform based on an easy-to-use hardware and software [4, 12]. The microcontroller board is designed and manufactured by several vendors. The boards have serial communications interfaces, including USB on some models to load programs from PCs.

In our model, the Arduino serves as a bridge between the PC and the interfacing circuit, which connects between the Arduino's digital pins and the geared DC motors that drive the wheelchair. When the Arduino receives a command/instruction from the computer, it causes the circuit to operate the motors and hence control the wheelchair. Those commands could be changed according to the Emotiv input as discussed earlier.

The software of the Arduino microcontroller is used to read and interpret the instructions and commands sent from a computer to the Arduino through the USB serial interface. There are two types of software. First, the Arduino-OSC communication is an OSC library called ArdOSC. OSC is the acronym for Open Sound Control, and it is a network protocol developed at CNMAT Center at the University of California at Berkeley. OSC is one of the most common protocols for communication among computers, sound synthesizers, and other multimedia devices that are optimized for modern networking technology and has been used in many application areas [59]. The "Mind your OSCs" application sends the data collected by the EPOC headset to any program that can receive and read OSC messages [52]. However, the Arduino Ethernet Shield hardware module is needed to be added to the system, which may be difficult to deal with. Second, Processing software was used to receive the OSC messages [6]. Processing is an easy-to-use, open-source programming environment and language that is used by novices, artists, and designers [6]. Programs written using Processing are called sketches. The reasons for using Processing software instead of ArdOSC library paradigm are as follows:

- (i) The OSC-P5 is a free open-source reliable OSC library for Processing software that allows the OSC data to be sent and received by Processing sketches [59].
- (ii) Processing software has an Arduino library that allows controlling the Arduino directly from Processing environment over serial communication by running the StandardFirmata Arduino sketch on the microcontroller. Hence, this combination has a high degree of compatibility [3, 6, 42].
- (iii) Processing software minimizes the power consumption, cost, and generated noise because there is no need for Arduino Ethernet Shield module addition.

3 Proposed System

This section describes the proposed model in detail. Generally, the main goal of an electrical wheelchair controller is the interpretation and processing of the driving commands to adapt the motor power; these commands flow among the user, PC, and digital controller. The proposed model aims to control the wheelchair either manually or automatically as shown in Figures 2 and 3. In the automatic mode, the standard wheelchair was controlled using either single-modal or multimodal approach. Using the single-modal approach, the wheelchair was controlled using a human head electric representation of the facial expressions, head movements, or EEG signals. In the multimodal approach, two or more signals were fused to control the wheelchair. In the manual mode, the wheelchair was controlled using a manual keypad as shown in Figures 2 and 3. In our model, the friction effect was neglected.



Figure 2: Block Diagram of the Proposed Wheelchair Control System.



Figure 3: Detailed Flowchart Diagram of the Proposed Wheelchair Control System.

Generally, the proposed system, brain-control wheelchair (BCW), used brain thoughts to control the wheelchair. When a user has a certain thought (push, pull, right, and left), the wheelchair moves in four predefined directions (forward, backward, turning right, and turning left, respectively). This control was implemented using a program installed on the Arduino microcontroller. Figure 4 shows the design of the wheelchair, whereas Figure 3 shows the proposed system to show how the chaired person can automatically or manually control the wheelchair.

3.1 Wheelchair Design

To achieve the goal of controlling an EPW, a number of mandatory modifications on the design of the standard wheelchair were implemented. As shown in Figure 4, a special woody shelf was added to hold the digital controller, switching control circuits, motors, gears, and high-capacity batteries including charging circuitry. There was also a special high-torque DC motor for each of the back wheels, two 12 V batteries, and an interfacing circuit between the motors and the Arduino microcontroller.



Figure 4: Modifications of the Standard Wheelchair to Suit the Proposed Brain-Controlled Battery-Powered Wheelchair Control Criteria.



Figure 5: Design of the Circuit that was Used to Drive the Motors.

The DC motors have two main problems. First, it sinks a level of current that normally cannot be offered directly from the output pin of a microcomputer chip or an Arduino. Therefore, they need some sort of driving and current boosting before controlling them. Second, the DC motors are a great source of interference that can make the rest of electronic devices misbehave. This problem can be solved by optically isolating the motor power supply.

In our proposed model, the two problems were solved using a simple circuit as shown in Figure 5. The controller output pin was connected to the anode terminal of an LED (D1) next to a photo transistor (Q1). D1 and Q1 provide an optical interfacing technique that was used to achieve a high level of isolation and hence solve the second problem. In addition, the motor sits between the relay contact and the 24 V power supply, allowing the DC motor to sink its rating current and thus solving the first problem. Table 1 illustrates the specifications of the components that were used in our proposed model.

3.2 Automatic BCW (ABCW)

The aim of the ABCW is to automatically control the movement of the wheelchair using different signals. As shown in Figure 3, the data flow of the proposed system starts by collecting the skull superficial signals using the EPOC headset, which collects data from three different modalities: head movements, facial expressions, and EEG signals. The collected signals are transferred from EPOC to PC through a Universal Serial Bus (USB) wireless transmitter/receiver channel, in which the commands are interpreted.

 Table 1: Components' Specifications for the Proposed Wheelchair System.

Head signals capturing device Emotiv EPOC headset Bluetooth wireless transmission to PC USB wireless recliver dongle Hydrator with 16 saline sensors Number of channels: 1a (pluc CMS/ORL references) Sampling method: sequential sampling, single ADC Sampling method: sequential sampling, single ADC Sampling rate: 128 Hz (2048 Hz internal) ADC resolution: 14-bit, 11 SB = 0.5 1 µV Bandwidth: 0.2–45 Hz Digital notch filters (S0/60 H2) Dynamic range (input refered): 256 mV (Vpp) Connectivity: Proprietary wireless, 2.4 GHz band Battery type: 1: Looply, 12 h lifterime PC (laptop) PC (laptop) Processor: Intel Core i7 3630Q Main memory: 8 68 Video graphics: NVIDIA GeForce GTX675MX Operating System: Microsoft Windows 8.1 Advino UND board Microcontroller board based on the ATmega328 14 digital input/vidupt pins 6 GPIO pins can be used as PWM outputs 6 analog inputs 6 GPIO pins can be used as PWM outputs 6 analog inputs 16 MHZ crystal oscillator USB bidirectional connection Manual steering controller Low-cost keypad 4 ON/OFF switches Sing transport Maximum voltage: 80 V Power: Power interface circuit Optical isolati	Component	Specifications
Bluetoth wireless transmission to PC USB wireless receiver dangle Hydrator with 16 saline sensors Number of channels: 14 (plus CMS/DRI references) Sampling method: sequentil sampling, single ADC Sampling rate: 128 Hz (2048 Hz internal) ADC resolution: 14-bit, 11SB = 0.51 µV Bandwidth: 0.2–45 Hz Digital notch filters (00/60 Hz) Upramic range (input referred): 256 mV (Vpp) Connectivity: Proprietary wireless, 2.4 GHz band Battery type: 1:poly, 12 h lifterime PC (laptop) Digital controller PC (laptop) PC (lap	Head signals capturing device	Emotiv EPOC headset
USB wireless receiver dongle Hydrator with 16 saline sensors Number of channels: 14 (plus CMS/DRL references) Sampling method: sequential sampling, siglet ADC Sampling reti-128 Hz (2048 Hz Internal) ADC resolution: 14-bit, 1L5B=0.51 µV Bandwidth: 0.2-45 Hz Digital notch filters (50/60 Hz) Dynamic range (input referred): 256 mV (Vpp) Connectivity: Proprietary wireless, 2.4 GHz band Battery type: Li-poly, 12 h lifetime PC (laptop) PC		Bluetooth wireless transmission to PC
Hydrator with 16 saline sensorsNumber of channels: 14 (plus CMS/DRL references)Sampling method: sequential sampling, single ADCSampling rate: 128 Hz (2048 Hz Internal)ADC resolution: 14-bit, 1158-0.51 µVBandwidth: 0.2-45 HzDigital notch filters (50/60 Hz)Dynamic range (input reference): 256 mV (Vpp)Connectivity: Proprietary wireless, 2.4 GHz bandBattery type: Li-poly, 12 h lifetimePC (laptop)PC (aptop)PC (aptop		USB wireless receiver dongle
Number of channels: 14 (plus CMS/DRL references)Sampling method: sequential sampling, single ADCSampling rate: 128 Hz (2048 Hz internal)ADC resolution: 14-bit, 1158-0.51 µVBandwidh: 0.2-45 HzDigital notch filters (50/60 Hz)Dynamic range (input referred): 256 mV (Vpp)Connectivity: Proprietary wireless, 2.4 GHz bandBattery type: Li-poly, 12 h lifetimePC (laptop)PC (laptop)PC (laptop)Porcessor: Intel Core 17 36300Main memory: 8 GBVideo graphics: MVIDIA Geforce GTK675MXOperating System: Microsoft Windows 8.1Digital controllerArduino UND boardMicrocontroller board based on the ATmega32814 digital input/output pins6 GPIO pins can be used as PWM outputs6 analog inputs16 MHz crystal oscillatorUSB bidirectional connectionIn-system programming (ISP) headerLow-cost Keypad4 ON/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitOptical isolation:Isolation test voltage: 5000 V _{mis} Interfaces With common logic familiesInput-output coupling capacitance: <0.5 pF		Hydrator with 16 saline sensors
Sampling method: sequential sampling, single ADC Sampling rate: 128 Hz (2048 Hz internal) ADC resolution: 14-bit, 1158-0.51 µV Bandwidth: 0.2-45 Hz Digital noth filters (50/60 Hz) Dynamic range (input referred): 256 mV (Vpp) Connectivity: Proprietary wireless, 2.4 GHz band Battery type: L-poly, 12 h lfetime PC (laptop) PC (aptop) PC cessor: Intel Core i7 3630Q Main memory: 8 GB Video graphics: NVIDIA GeForce GTX675MX Operating System: Microsoft Windows 8.1 Arduino UNO board Digital controller Arduino UNO board Microcontroller board based on the ATmega328 14 digital input/output pins 6 GBNO pins can be used as PWM outputs 6 analog inputs 16 GH2 pins can be used as PWM outputs 6 analog linputs 16 MHz crystal oscillator USB bidirectional connection Hn-system programming (ISP) header Low-cost keypad 4 ON/OFF switches Switch labels: forward, backward, right, and left Power interface circuit Solation test voltage: 5000 V _{mas} Interfaces with common logic families Input-output coupling capacitance: <-0.5 pF Current boosting: Darlington pair power transistors Current taing: 10 A Maximum voltage: 80 V Power: 150 W Electric wheelchair DC motors Rated voltage: 24 VDC Rated speed: 4300 rpm No load speed: 5000 rpm No load speed: 500 rpm No load		Number of channels: 14 (plus CMS/DRL references)
Sampling rate: 128 Hz (2048 Hz internal)ADC resolution: 14-bit, 1 LSB = 0.51 µVBandwidh: 0.2–45 HzDigital notch filters (50/60 Hz)Dynamic range (input refered): 256 mV (Vpp)Connectivity: Proprietary wireless, 2.4 GHz bandBattery type: Li-poly, 12 h lifetimePC (laptop)PC (laptop)PC (laptop)Digital controllerAduino UNO boardMicrocontroller System: Microsoft Windows 8.1Aduino UNO boardMicrocontroller board based on the ATmega32814 digital input/output pins6 GPIO pins can be used as PWM outputs6 analog inputs16 MHz crystal oscillatorUSB bidirectional connectionIn-system programming (ISP) headerLow-cost keypad4 00/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitPower interface circuitPower: interface with common logic familiesInput-output coupling capacitance: <0.5 pF		Sampling method: sequential sampling, single ADC
ADC resolution: 14-bit, 1158 = 0.51 µVBandwidth: 0.2-45 HzDigital notch filters (50/60 H2)Dynamic range (input referred): 256 mV (Vpp)Connectivity: Proprietary wireless, 2.4 GHz bandBattery type: Li-poly, 12 h lifetimePC (laptop)PC (aptop)PC (aptop)Patter (aptop)Pc (aptop) <td></td> <td>Sampling rate: 128 Hz (2048 Hz internal)</td>		Sampling rate: 128 Hz (2048 Hz internal)
Bandwidh: 0.2 - 45 HzDigital notch filters (50/60 Hz)Dynamic range (input referred): 256 mV (Vpp)Connectivity: Proprietary wireless, 2.4 GHz bandBattery type: Li-poly, 12 h lifetimePC (laptop)PC (laptop)Power interface (laptop)Power interface (laptop)Power interface (laptop)Power int		ADC resolution: 14-bit, 1 LSB = 0.51 μ V
Digital notch filters (50/60 Hz) Dynamic range (input referred): 250 mV (Vpp) Connectivity: Proprietary wireless, 2.4 GHz band Battery type: Li-poly, 12 h lifetimePC (laptop)Processor: Intel Core i7 3630Q Main memory: 8 GB Video graphics: NVIDIA Geforce GTK675MX Operating System: Microsoft Windows 8.1Digital controllerArduino UNO board Microcontroller board based on the ATmega328 14 digital input/output pins 6 GPI0 pins can be used as PWM outputs 6 analog inputs 16 Maz crystal oscillator USB bidirectional connection In-system programming (ISP) header Low-cost keypad 4 0N/OFF switchesPower interface circuitSwitch labels: forward, backward, right, and left Optical isolation: Isolation: <td></td> <td>Bandwidth: 0.2–45 Hz</td>		Bandwidth: 0.2–45 Hz
PC (laptop) PC (la		Digital notch filters (50/60 Hz)
PC (laptop)Connectivity: Proprietary wireless, 2.4 GHz band Battery type: Li-poly, 12 h lifetime Processor: Intel Core 73 6300 Main memory: 8 GB Video graphics: NVIDIA Gefore GTK675MX Operating System: Nicrosoft Windows 8.1Digital controllerArduino UNO board Microsontroller board based on the ATmega328 14 digital input/output pins 6 GPI0 pins can be used as PWM outputs 6 analog inputs 16 MHz crystal oscillator US8 bidirectional connection In-system programming (ISP) header In-system programming (ISP) headerManual steering controllerDytein South abeed on the ATmega328 14 digital input/output pins 6 GPI0 pins can be used as PWM outputs 6 analog inputs 16 MHz crystal oscillator US8 bidirectional connection In-system programming (ISP) header In-system programming (ISP) header In-system programming (ISP) header In-system programming (ISP) header Input-output coupling capacitance: <0.5 pF Current boosting: Current boosting: Current boosting: Current boosting: Current boosting: Current boosting: Current boosting: Current boosting: Current boosting: Current ing 10 A Maximum voltage: 80 V Power: 150 WElectric wheelchair DC motorsRated speed: 4300 rpm No load speed: 5500 rpm No load speed: 5500 rpm No load speed: 5000 rpm No load speed: 5000 rpm No load speed: 5000 rpm No load speed: 5500		Dynamic range (input referred): 256 mV (Vpp)
Battery type: Li-poly, 12 h lifetimePC (laptop)Processor: Intel Core i7 3630QMain memory: 8 6BVideo graphics: NVIDIA GeForce GTX675MXDigital controllerArduino UNO boardDigital controllerArduino UNO boardMicrocontroller board based on the ATmega32814 digital input/output pins6 GPIO pins can be used as PWM outputs6 analog inputs16 MHz crystal oscillatorUSS bidirectional connectionIn-system programming (ISP) headerManual steering controllerLow-cost keypad4 ON/OFF switchesPower interface circuitOptical isolation: Isolation test voltage: 5000 V _{axis} Interfaces with coupling capacitance: <0.5 pF		Connectivity: Proprietary wireless, 2.4 GHz band
PC (laptop) Processor: Intel Core i7 3630Q Main memory: 8 GB Video graphics: NVDA Geforce GTX675MX Operating System: Microsoft Windows 8.1 Arduino UNO board Microcontroller oard based on the ATmega328 14 digital input/output pins 6 GPIO pins can be used as PWM outputs 6 analog inputs 6 GPIO pins can be used as PWM outputs 6 analog inputs 16 MHz crystal oscillator USB bidirectional connection In-system programming (ISP) header Low-cost keypad 4 ON/OFF switches Switch labels: forward, backward, right, and left Optical isolation: Isolation test voltage: 5000 V _{asts} Interface circuit Power interface circuit Isolation test voltage: 5000 V _{asts} Interfaces with common logic families Input-output coupling capacitance: <0.5 pF Current taing: 10 A Maximum voltage: 80 V Power: 150 W Electric wheelchair DC motors Rated speed: 4300 rpm No load current: 1.2 A Rated orgue: 500 rpm No load current: 1.2 A Rated cu		Battery type: Li-poly, 12 h lifetime
Main memory: 8 GBVideo graphics: NVIDIA GeFore GTX675MXOperating System: Microsoft Windows 8.1Arduino UNO boardMicrocontroller board based on the ATmega32814 digital input/output pins6 GPIO pins can be used as PWM outputs6 analog inputs16 MHz crystal oscillatorUSB bid/rectional connectionIn-system programming (ISP) headerManual steering controllerLow-cost keypad4 ON/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitOptical isolation:Isolation test voltage: 5000 V _{puts} Interfaces with common logic familiesInput-output coupling capacitance: <0.5 pF	PC (laptop)	Processor: Intel Core i7 3630Q
Video graphics: NVIDIA GeForce GTX675MX Operating System: Microsoft Windows 8.1Digital controllerArduino UNO boardMicrocontroller board based on the ATmega328 14 digital input/output pins 6 GPIO pins can be used as PWM outputs 6 analog inputs 16 MHz crystal oscillator USB bidirectional connection In-system programming (ISP) header Low-cost keypad 4 ON/OFF switches Switch labels: forward, backward, right, and left Soliton to used aspectation: Isolation tet voltage: 5000 V _{Pass} Interface circuitPower interface circuitOptical isolation: Isolation tet voltage: 5000 V _{Pass} Interfaces with common logic families Input-output coupling capacitance: <0.5 pF Current bosting: Darlington pair power transistors Current tassitors Current based voltage: 80 V Power: 150 WElectric wheelchair DC motorsRated voltage: 24 VDC Rated speed: 4300 rpm No load speed: 500 rpm/V No load right speed No load right speed No l		Main memory: 8 GB
Digital controllerOperating System: Microsoft Windows 8.1Digital controllerArduino UNO boardMicrocontroller board based on the ATmega32814 digital input/output pins6 GPIO pins can be used as PWM outputs6 analog inputs6 GPIO pins can be used as PWM outputs6 analog inputs16 MHz crystal oscillatorUSB bidirectional connectionUnsystem programming (ISP) headerIn-system programming (ISP) headerManual steering controllerLow-cost keypad4 ON/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitOptical isolation:Isolation test voltage: 5000 V _{eass} Interfaces with common logic familiesInterfaces with common logic familiesInterfaces: 80 VPower: 150 WRated speed: 300 rpmElectric wheelchair DC motorsRated speed: 24 VDCRated speed: 24 VDCRated speed: 24 VDCRated corrent: 1.2 ARated corrent: 1.2 ARated power: 247.6 WMaximum officiency: 84%Torque constant: 46 mNm/ASpeed constant: 208 rpm/VRotor inertia: 1000Steed constant: 200 rpm		Video graphics: NVIDIA GeForce GTX675MX
Digital controllerArduino UNO boardMicrocontroller board based on the ATmega32814 digital input/output pins6 GPIO pins can be used as PWM outputs6 analog inputs16 MHz crystal oscillatorUSB bidirectional connectionIn-system programming (ISP) headerManual steering controllerManual steering controllerPower interface circuitOptical isolation:Isolation test voltage: 5000 V _{BMS} Interfaces with commo logic familiesInput-output coupling capacitance: <0.5 pF		Operating System: Microsoft Windows 8.1
Microcontroller board based on the ATmega328 14 digital input/output pins 6 GPIO pins can be used as PWM outputs 6 analog inputs 16 MHz crystal oscillator USB bidirectional connection In-system programming (JSP) header Low-cost keypad 4 ON/OFF switches Switch labels: forward, backward, right, and left Optical isolation: Switch labels: forward, backward, right, and left Optical isolation: Instraces with common logic families Input-output coupling capacitance: <0.5 pF Current boosting: Darlington pair power transistors Current tating: 10 A Maximum voltage: 80 V Power: 150 W Electric wheelchair DC motors Rated voltage: 24 VDC Rated voltage: 24 VDC Rated voltage: 5000 rpm No load speed: 3000 rpm No load speed: 3000 rpm No load current: 1.2 A Rated current: 14 A Rated current: 14A Rated current: 14A Rated power: 247.6 W Maximum efficiency: 84% Torque constant: 268 rpm/V Rotor inerti: 2000	Digital controller	Arduino UNO board
14 digital input/output pins6 GPIO pins can be used as PWM outputs6 analog inputs16 MHz crystal oscillatorUSB bidirectional connectionIn-system programming (ISP) headerLow-cost keypad4 ON/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitOptical isolation:Isolation test voltage: 5000 V _{aus} Interfaces with common logic familiesInput-output coupling capacitance: <0.5 pF		Microcontroller board based on the ATmega328
6 GPIO pins can be used as PWM outputs6 analog inputs16 MHz crystal oscillatorUSB bidirectional connectionIn-system programming (ISP) headerManual steering controllerLow-cost keypad4 ON/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitOptical isolation:Isolation test voltage: 5000 V _{RMS} Interfaces with common logic familiesInput-output coupling capacitance: <0.5 pF		14 digital input/output pins
6 analog inputs 16 MHz crystal oscillator USB bidirectional connection In-system programming (ISP) header Low-cost keypad 4 ON/OFF switches Switch labels: forward, backward, right, and left Optical isolation: Isolation test voltage: 5000 V _{eMS} Interfaces with common logic families Input-output coupling capacitance: <0.5 pF Current boosting: Darlington pair power transistors Current rating: 10 A Maximum voltage: 80 V Power: 150 W Electric wheelchair DC motors Rated voltage: 24 VDC Rated speed: 4300 rpm No load speed: 5000 rpm No load speed: 5500 mNm Rated current: 11 A Rated current: 11 A Rated current: 12 A Rated current: 24 M Rated current: 44 A Rated current: 44 A Rated current: 44 A Rated current: 44 A Rated current: 46 MNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		6 GPIO pins can be used as PWM outputs
16 MHz crystal oscillatorUSB bidirectional connectionIn-system programming (ISP) headerLow-cost keypad4 ON/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitOptical isolation:Isolation test voltage: 5000 V _{RMS} Interfaces with common logic familiesInput-output coupling capacitance: <0.5 pF		6 analog inputs
USB bidirectional connectionIn-system programming (ISP) headerManual steering controllerLow-cost keypad4 0N/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitOptical isolation:Isolation test voltage: 5000 V _{RMS} Interfaces with common logic familiesInput-output coupling capacitance: <0.5 pF		16 MHz crystal oscillator
Manual steering controllerIn-system programming (ISP) headerManual steering controllerLow-cost keypad4 ON/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitOptical isolation:Isolation test voltage: 5000 V_MMSInterfaces with common logic familiesInput-output coupling capacitance: <0.5 pF		USB bidirectional connection
Manual steering controllerLow-cost keypad 4 0N/OFF switches Switch labels: forward, backward, right, and leftPower interface circuitOptical isolation: Isolation test voltage: 5000 VRMS Interfaces with common logic families Input-output coupling capacitance: <0.5 pF Current boosting: Darlington pair power transistors Current rating: 10 A Maximum voltage: 80 V Power: 150 WElectric wheelchair DC motorsRated voltage: 24 VDC Rated speed: 4300 rpm No load speed: 5000 rpm No load current: 1.2 A Rated torque: 550 mNm Rated power: 247.6 W Maximum efficiency: 84% Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		In-system programming (ISP) header
4 0N/OFF switchesSwitch labels: forward, backward, right, and leftPower interface circuitOptical isolation: Isolation test voltage: 5000 V _{RMS} Interfaces with common logic families Input-output coupling capacitance: <0.5 pF Current boosting: Darlington pair power transistors Current rating: 10 A Maximum voltage: 80 V Power: 150 WElectric wheelchair DC motorsRated voltage: 24 VDC Rated speed: 4300 rpm No load speed: 5000 rpm No load current: 1.2 A Rated current: 1.2 A Rated current: 1.4 A Rated power: 247.6 W Maximum efficiency: 84% Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000	Manual steering controller	Low-cost keypad
Switch labels: forward, backward, right, and leftPower interface circuitOptical isolation: Isolation test voltage: 5000 VRMS Interfaces with common logic families Input-output coupling capacitance: <0.5 pF Current boosting: Darlington pair power transistors Current rating: 10 A Maximum voltage: 80 V Power: 150 WElectric wheelchair DC motorsRated voltage: 24 VDC Rated speed: 4300 rpm No load speed: 5000 rpm No load speed: 5000 rpm No load current: 1.2 A Rated current: 1.2 A Rated torque: 550 mNm Rated torque: 550 mNm Rated torque: 550 mNm Rated torque: 547.6 W Maximum efficiency: 84% Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		4 ON/OFF switches
Power interface circuitOptical isolation: Isolation test voltage: 5000 VRMS Interfaces with common logic families Input-output coupling capacitance: <0.5 pF Current boosting: Darlington pair power transistors Current rating: 10 A Maximum voltage: 80 V Power: 150 WElectric wheelchair DC motorsRated voltage: 24 VDC Rated speed: 4300 rpm No load speed: 5000 rpm No load speed: 5000 rpm No load current: 1.2 A 		Switch labels: forward, backward, right, and left
Isolation test voltage: 5000 V _{EMS} Interfaces with common logic familiesInput-output coupling capacitance: <0.5 pF	Power interface circuit	Optical isolation:
Interfaces with common logic familiesInput-output coupling capacitance: <0.5 pF		Isolation test voltage: 5000 V _{RMS}
Input-output coupling capacitance: <0.5 pFCurrent boosting:Darlington pair power transistorsCurrent rating: 10 AMaximum voltage: 80 VPower: 150 WElectric wheelchair DC motorsRated voltage: 24 VDCRated speed: 4300 rpmNo load speed: 5000 rpmNo load current: 1.2 ARated torque: 550 mNmRated power: 247.6 WMaximum efficiency: 84%Torque constant: 46 mNm/ASpeed constant: 208 rpm/VRotor inertia: 1000		Interfaces with common logic families
Current boosting:Darlington pair power transistorsCurrent rating: 10 AMaximum voltage: 80 VPower: 150 WElectric wheelchair DC motorsRated voltage: 24 VDCRated speed: 4300 rpmNo load speed: 5000 rpmNo load current: 1.2 ARated current: 1.4 ARated torque: 550 mNmRated power: 247.6 WMaximum efficiency: 84%Torque constant: 46 mNm/ASpeed constant: 208 rpm/VRotor inertia: 1000		Input-output coupling capacitance: <0.5 pF
Darlington pair power transistorsCurrent rating: 10 AMaximum voltage: 80 VPower: 150 WElectric wheelchair DC motorsRated voltage: 24 VDCRated speed: 4300 rpmNo load speed: 5000 rpmNo load current: 1.2 ARated current: 14 ARated torque: 550 mNmRated power: 247.6 WMaximum efficiency: 84%Torque constant: 46 mNm/ASpeed constant: 208 rpm/VRotor inertia: 1000		Current boosting:
Current rating: 10 AMaximum voltage: 80 VPower: 150 WElectric wheelchair DC motorsRated voltage: 24 VDCRated speed: 4300 rpmNo load speed: 5000 rpmNo load current: 1.2 ARated current: 14 ARated torque: 550 mNmRated power: 247.6 WMaximum efficiency: 84%Torque constant: 46 mNm/ASpeed constant: 208 rpm/VRotor inertia: 1000		Darlington pair power transistors
Maximum voltage: 80 VPower: 150 WElectric wheelchair DC motorsRated voltage: 24 VDCRated speed: 4300 rpmNo load speed: 5000 rpmNo load current: 1.2 ARated current: 14 ARated torque: 550 mNmRated power: 247.6 WMaximum efficiency: 84%Torque constant: 46 mNm/ASpeed constant: 208 rpm/VRotor inertia: 1000		Current rating: 10 A
Power: 150 WElectric wheelchair DC motorsRated voltage: 24 VDCRated speed: 4300 rpmNo load speed: 5000 rpmNo load current: 1.2 ARated current: 1.4 ARated torque: 550 mNmRated power: 247.6 WMaximum efficiency: 84%Torque constant: 46 mNm/ASpeed constant: 208 rpm/VRotor inertia: 1000		Maximum voltage: 80 V
Electric wheelchair DC motorsRated voltage: 24 VDCRated speed: 4300 rpmNo load speed: 5000 rpmNo load current: 1.2 ARated current: 14 ARated torque: 550 mNmRated power: 247.6 WMaximum efficiency: 84%Torque constant: 46 mNm/ASpeed constant: 208 rpm/VRotor inertia: 1000		Power: 150 W
Rated speed: 4300 rpmNo load speed: 5000 rpmNo load current: 1.2 ARated current: 14 ARated torque: 550 mNmRated power: 247.6 WMaximum efficiency: 84%Torque constant: 46 mNm/ASpeed constant: 208 rpm/VRotor inertia: 1000	Electric wheelchair DC motors	Rated voltage: 24 VDC
No load speed: 5000 rpm No load current: 1.2 A Rated current: 14 A Rated torque: 550 mNm Rated power: 247.6 W Maximum efficiency: 84% Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		Rated speed: 4300 rpm
No load current: 1.2 A Rated current: 14 A Rated torque: 550 mNm Rated power: 247.6 W Maximum efficiency: 84% Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		No load speed: 5000 rpm
Rated current: 14 A Rated torque: 550 mNm Rated power: 247.6 W Maximum efficiency: 84% Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		No load current: 1.2 A
Rated torque: 550 mNm Rated power: 247.6 W Maximum efficiency: 84% Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		Rated current: 14 A
Rated power: 247.6 W Maximum efficiency: 84% Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		Rated torque: 550 mNm
Maximum efficiency: 84% Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		Rated power: 247.6 W
Torque constant: 46 mNm/A Speed constant: 208 rpm/V Rotor inertia: 1000		Maximum efficiency: 84%
Speed constant: 208 rpm/V Rotor inertia: 1000		Torque constant: 46 mNm/A
Rotor inertia: 1000		Speed constant: 208 rpm/V
		Rotor inertia: 1000

3.2.1 Command Interpreter

Driving commands are usually issued by the acquisition facilities of the wheelchair such as joysticks, voice recognizer, or head movement sensors [58]. These commands are divided into two categories: jump type and step type. In the jump-type category, the command will load a fixed speed such as back, go, and stop

commands. In the step-type commands, the speed and direction of the wheelchair are changed such as moving left, right, forward, and backward commands. In this study, the command interpreter receives the signals that were sent from EPOC, and the Emotiv SDK processes the data stream received through the USB inlet and converts it into accessible packets of data that can be processed and interpreted using the generic software packages. Based on the interpretation of the instantly received data, the computer issues a predefined control instruction and sends a command message to another USB outlet, which transfers the command to an Arduino microcontroller that was programmed to handle these commands and to move the wheelchair forward, backward, left, or right automatically. The controller is responsible for controlling two high-torque geared optically isolated battery-powered DC motors, and the DC motors can efficiently move and steer a loaded wheelchair. Figure 1 demonstrates the setup of the Emotiv EPOC headset to control the intelligent wheelchair for assisting the locked-in subjects.

Interface buses labeled "A" to "E" act as block connectors. Generally speaking, in Figure 6, the buses are not necessarily carrying only the electric signals. Paths "A" and "E" are the physical information flow associated with the user's reaction, e.g. the commands from the facial expression, head movements, and EEG signals. Bus "E" carries the feedback information about the position of the wheelchair. Bus "B" contains the signals that were collected from the Emotiv EPOC headset, bus "D" has the energized PWM signals, and bus "C" contains the interpreted commands. Through the interface of these buses, the system forms a closed-loop control flow.

3.2.2 Single-Modal vs. Multimodal BCW

This paper proposes an approach for controlling the wheelchair for a single preprogrammed movement (single output) using a combination of two or more certain input signals (multiple inputs) as an example for the multimodal wheelchair control. Figure 7 demonstrates the idea of input control signal fusion to extract a single decision for the chair movement.

In the single-modal approach, the wheelchair was controlled using only one signal (facial expression, head movement, or EEG signals), whereas, in the multimodal approach, a fusion scheme was adopted using a group of summing circuits that merge a number of single-modality signals into a unique control signal. Combining different signals can allow an effective and functional interaction for people with limited mobility/coordination abilities or under specific conditions. In other words, the multimodal approach was used to exploit all the head movements, facial expressions, and mind thoughts to allow a large number of users with different degrees of disability to use the proposed application. Hence, the multimodal approach is flexible for different possible users' needs. For example, if the subject cannot perform a specific head movement, the proposed approach should be able to replace the head movement with facial expressions or thought. In our implementation, it was assumed that all the incoming signals have the same weight and the signals were combined using the simple sum-rule fusion technique [32, 33].



Figure 6: Block Diagram of the Wheelchair Controller System.



Figure 7: Design of the Controller Block Diagram.



Figure 8: Manual Control Mode Based on Keypad to Control the Intelligent Wheelchair Manually.

Figure 7 demonstrates the proposed system software controller block diagram. In case of unimodal or single-modal control, only one input signal amplitude should exceed the threshold value to enable the chaired person to steer the chair to a prescribed direction. With the multimodal alternative, a subset of input signal amplitudes must overcome the threshold barrier for guaranteeing a controller's final decision for a certain movement.

3.3 Manual Wheelchair Control Model (MWCM)

In the manual control mode, a keypad was designed using four ON/OFF switches to control the movement of the wheelchair to left, right, forward, or backward. The designed keypad sends commands or signals directly to the DC motors that control the wheelchair movements. It could be attached to any of the chair armrest (i.e. right or left armrests) as the user prefer (see Figure 8).

4 Experimental Results and Testing Scenarios

To test the proposed solutions, a number of experiments were conducted to simulate how chaired individuals control the wheelchair through either automatic (using single-modal and multimodal approaches) or manual control modes. The next two subsections present the experiments' environment and the conducted experiments and their results.



Figure 9: First Trajectory (with 19.9 m Overall Length) for Testing the Wheelchair Control Performance.



Figure 10: Second Trajectory (with 58.3 m Length) for Evaluating the Proposed System Efficiency.

4.1 Experimental Setup

In all conducted experiments: a laptop was installed on a wheelchair in front of the sitting person, and the 14-electrode Emotiv EPOC headset was used to collect the person's head impressions from the skull surface. The superficially picked-up signals, containing the brain thoughts, head gestures, and facial emotions, were electrically encoded and then wirelessly sent to a PC through the Arduino microcontroller to be interpreted and then translated into useful control instructions. The experiments were conducted on a flat terrain and indoor environment. All such experiments have the following components:

- Two trajectories with different lengths: The subjects were asked to follow two different trajectories; each trajectory has a starting point and an ending point. The first trajectory, as shown in Figure 9, is short (length = 19.9 m) and easy to track and has one obstacle to move around. The other trajectory, as shown in Figure 10, is more difficult to track and it has a length equal to 58.3 m and three obstacles to move around, i.e. the subjects need to change their directions' movement many times.
- Two chaired volunteers/subjects: one male and another female were asked to test our proposed solution. The volunteers had no prior experience with our proposed wheelchair control systems, thus making our experiment very close to a real scenario. They were asked to repeat each experiment three times. Hence, there were 12 different experiments, 2 (volunteers)×2 (trajectories)×3 trails, to evaluate our model.
- Graphical user interface (GUI): To improve the usability of our proposed systems, a GUI was provided using the Processing programming language. This GUI appears and works as a guide to the user to suit-



Figure 11: GUI of the Automatic Control Mode.

The Resultant Control Signal Strength While the User is Thinking About Left; This Control Signal Instructs the BCW Left and Right Back Wheel Motors to Rotate Clockwise 45°.

ably and accordingly generate the desired commands, while the resultant decisions are displayed on the PC screen, as seen in Figure 11. The set of all possible commands, used in all experiments, is as follows:

- Left: The right and left DC motors are powered to rotate the right wheel of the chair in the forward direction and the left wheel to the backward direction.
- Right: The left and right DC motors are powered to rotate the left wheel of the chair in the forward direction and the right wheel to the backward direction.
- Forward: The two DC motors are powered to rotate both wheels in the forward direction.
- Backward: The two DC motors are powered to rotate both wheels in the backward direction.

4.1.1 Assessment Methods

Three different assessment methods were used to evaluate our experiments. The first was the mean deviation from the real trajectory and it was modeled as follows: $m = \sum_{i=1}^{N} \epsilon_i$, where *N* represents the number of trails and ϵ_i is the total error or deviation of the *i*th trail between the simulated trajectory and the real one. The error between two trajectories/paths can be calculated using path metrics such as the Hausdorff or Fréchet distances [28]. The path metric is a function of two paths, and it returns a distance between the two paths. Some individual points are first selected on both trajectories, and then the difference between these points is calculated. The distance represents the sum of all differences. The two paths are identical if the distance is zero, and large distance indicates dissimilarity. The second method is the standard deviation, and it was modeled as the errors of all trails for the same subject. The third is the average error, and it was modeled as the ratio between the mean deviation and the length of the trajectory, i.e. $Avg = \frac{m}{L}$, where *L*

represents the length of the trajectory. The length of the first and second trajectories was 19.9 and 58.3, respectively.

4.2 Conducted Experiments and Their Results

Three different experiments were conducted for the proposed system performance evaluation. In the first experiment, the two subjects were asked to control the wheelchair manually. In the second and third

Subjects	Trails	Automatic single-modal approach					Manual control		
		Head movements		Facial expressions		EEG signals			
		Tr. #1	 Tr. #2	Tr. #1	Tr. #2	Tr. #1	 Tr. #2	Tr. #1	Tr. #2
Subject 1	1	2.4	7	2.56	7.54	3.45	9.85	1.45	4.1
	2	2.15	6.62	2.42	7.12	3.25	9.74	1.15	3.92
	3	2.1	6.13	2.31	6.84	3.1	9.74	1.13	3.82
Mean (standard deviation)		2.22 (0.16)	6.58 (0.44)	2.43 (0.13)	7.17 (0.35)	3.27 (0.18)	9.78 (0.06)	1.24 (0.18)	3.94 (0.15)
Subject 2	1	3.2	7.1	2.5	7.42	3.48	9.68	1.42	4.00
	2	2.05	6.5	2.45	7.13	3.41	9.5	1.21	3.94
	3	2.05	6.05	2.3	7.01	3.2	9.5	1.12	3.85
Mean (staı deviation)	ndard	2.13 (0.14)	6.55 (0.53)	2.42 (0.1)	7.19 (0.21)	3.36 (0.15)	9.56 (0.10)	1.25 (0.15)	3.93 (0.08)
Average er	r ror (%)	10.93	11.26	12.19	12.32	16.66	16.59	6.26	6.75

 Table 2:
 Mean and Standard Deviation of the Distance Between the Simulated Movements and the Two Trajectories Using
 Single-Modal Signals and Manual Control Mode.

Tr. #1, first trajectory; Tr. #2, second trajectory.

experiments, the subjects were asked to first control the wheelchair using the single-modal approach and then using the multimodal approach. The descriptions of each experiment are explained in the next sections.

4.2.1 Control the Wheelchair Using Manual Keypad

In this experiment, the wheelchair was controlled manually using a keypad. This experiment was conducted to show how the wheelchair is controlled using the keypad commands, which were generated from the two subjects to track the two trajectories. The results of this experiment are summarized in Table 2.

4.2.2 Control the Wheelchair Using the Single-Modal Approach

In this experiment, single-modal signals were used to control the wheelchair. This experiment has three subexperiments, which were conducted to compare different single-modal signals, i.e. when using either head movement, facial expressions, or EEG signals to control the wheelchair. In all subexperiments, two subjects were asked to control the movement of the wheelchair to follow the two trajectories in Figures 9 and 10 for three times. In the first subexperiment (using head movement), left, right, up, and down head movements were used to move the wheelchair left, right, forward, and backward, respectively. In the second subexperiment (using facial expressions), happy, anger, surprise, and fear expressions were used to move the wheelchair left, right, forward, and backward, respectively. In the third experiment (using ECG signals), the subjects were asked to think to move left, right, forward, and backward, which generates EEG signals that were used to control the directions' movement of the wheelchair. Table 2 summarizes the results of this experiment.

4.2.3 Control the Wheelchair Using the Multimodal Approach

In this experiment, multimodal signals were used to control the wheelchair by combining or fusing two signals. In this experiment, three subexperiments were conducted. In each subexperiment, the two subjects

Subjects	Trails		FE+EEG		HM + EEG	HM+FE		
		Tr. #1	Tr. #2	Tr. #1	Tr. #2	Tr. #1	Tr. #2	
Subject 1	1	2.20	5.98	1.89	6.84	1.82	5.4	
	2	2.10	5.94	1.84	6.91	1.75	5.24	
	3	1.98	6.01	1.75	6.75	1.64	5.20	
Mean (standa deviation)	ard	2.09 (0.11)	5.98 (0.35)	1.83 (0.07)	6.83 (0.08)	1.74 (0.09)	5.28 (0.11)	
Subject 2	1	2.05	6.12	1.95	6.67	1.74	5.64	
	2	2.05	6.15	1.92	6.65	1.72	5.51	
	3	1.84	6.02	1.92	6.65	1.68	5.27	
Mean (standa deviation)	ard	1.98 (0.12)	6.10 (0.07)	1.93 (0.02)	6.66 (0.01)	1.71 (0.03)	5.47 (0.19)	
Average error	r (%)	10.23	10.36	9.45	11.57	8.67	9.22	

Table 3: Mean and Standard Deviation of the Distance Between the Simulated Movements and the Two Trajectories Using Multimodal Control Signals.

FE, facial expression; HM, head movement.

were asked to control the wheelchair to track the two trajectories by combining between (1) facial expressions and EEG signals (FE + EEG), (2) head movements and EEG signals (HM + EEG), and (3) head movements and facial expressions (HM + FE). The performance evaluation of these experiments is shown in Table 3.

4.3 Discussion

The results summarized in Tables 2 and 3 will be discussed in this section. The results in Table 2 show the deviation between the simulated movements and the two trajectories using manual mode and the single-modal approach, whereas Table 3 shows the results of the multimodal approach. From these two tables, the following remarks can be drawn.

- (i) A comparison between the results of the automatic single-modal signals and the manual mode showed that the average error rate of the manual control mode ranged from 6.26% to 6.75%, whereas the average error rate using the single-modal approach was more than 10%. It is not surprising that the wheelchair using manual control is more accurate than all other single-modal signals. However, the important finding was that the single-modal approach achieved a relatively low average rate. Hence, it solves the problem of disabled people who may not be able to manually control using conventional joysticks or keypads.
- (ii) A comparison between the results of the single-modal signals showed that the mean deviation of the head movement, facial expressions, and EEG signals from the first trajectory were 2.18,¹ 2.43, and 3.32 m, respectively, whereas, in the second trajectory, the deviation of the head movement, facial expressions, and EEG signals was 6.57, 7.18, and 9.67 m, respectively. Moreover, the average errors of the head movements ranged from 10.93% to 11.26%, facial expression errors ranged from 12.19% to 12.32%, and EEG signals ranged from 16.59% to 16.66%. From these results, we can conclude that controlling the wheel-chair using head movements simulated the two trajectories better than the other two signals. Therefore, the head movement is accurate and suitable for controlling wheelchair than the two other signals. This is because (1) the EEG signals are weak and may be affected by different sources such as physiological sources, which are generated from the body parts having an electric dipole such as heart, eyes, muscle,

¹ For example, the mean deviation of the head movement is calculated by taking the ratio of the mean deviation of the two subjects as follows: $=\frac{2.22+2.13}{2}\approx 2.18$.

and tongue, or nonphysiological sources, which are caused by body or electrode movements [58], and (2) facial expressions depend mainly on facial muscle movements. However, these movements depend on the individuals' actions. Moreover, extreme/strong expressions (e.g. smiling expression) can be detected and decoded easier than weak expressions such as anger expression [24, 37].

- (iii) In Table 3, comparing the multimodal signals, it can be noticed that the mean deviation of the FE+EEG, HM+EEG, and HM+FE from the first trajectory was 2.03, 1.88, and 1.725 m, respectively, whereas, in the second trajectory, the deviation of the FE+EEG, HM+EEG, and HM+FE signals were 6.04, 6.75, and 5.38 m, respectively. In other words, using the HM+FE gave more accurate results than the other two multimodal signals. The reason is that head movements and facial expressions are more accurate than EEG signals.
- (iv) Comparing single-modal and multimodal approaches showed that the multimodal approach achieved mean deviation lower than all single-modal signals. For example, the average error of the HM+EEG ranged from 9.45% to 11.57%, whereas the EEG ranged from 16.66% to 16.59% and HM ranged from 10.93% to 11.26%. Hence, combining two or more different signals generates a new signal that was more robust against artifacts and noises as reported in Ref. [2]. Hence, the problem of weakness of signals or noise is solved by combining two or more signals together.
- (v) Comparing the results of the two trajectories, it can be seen that there is a slight difference between the average error of the two trajectories, which reflects that the performance of the proposed approaches (i.e. single modal and multimodal) is stable and suitable for short or long trajectories and it is affected slightly by the number of obstacles.

In short, from the above discussion, it can be concluded that (1) the manual model was more accurate than all other automatic models; (2) the multimodal signal control achieved a low average error compared to the single-modal one; (3) the facial expressions combined with head movements (HM + FE) achieved minimum error (this is summarized in Figure 12); (4) in the single-modal approach, the head movements achieved the best results, whereas the EEG signal achieved the worst results; and (5) the average error rate of the single-modal and multimodal approaches was slightly affected by the length of the trajectories. Hence, it can be said that the proposed model is suitable for chaired people.

5 Conclusions and Future Work

In this paper, a novel wheelchair control system was proposed. This system made use of mind thoughts using its EEG signals, facial expressions, and head gestures to allow the chaired person to manually or automati-



Figure 12: Comparison Between the Accuracy of Manual and Automatic (Single-Modal and Multimodal) Control Modes.

cally control of his/her wheelchair. The aim of the proposed system was realized using hardware (wheelchair, Emotiv EPOC EEG headset, and Arduino microcontroller) and software (Processing language). Real experiments were conducted under different levels of trajectories and various modes of wheelchair controls. Also, comparisons between manual and automatic modes were conducted. The obtained results showed that the manual control mode was more accurate than all other automatic approaches and the former was easy to use by the subjects using a GUI interface. Also, the multimodal control approach decreased the deviation from the real trajectories and achieved results better than all other single-modal controls, whereas facial expressions along with head movements achieved the minimum error. The main advantages of the proposed system were that, using different signals (EEG, head movements, and facial expression), the proposed system could support a high degree of customization to suit many degrees of disability, low cost, ergonomics, and easy control and be provided with a PC screen. In the future work, it is planned to add two other features to the system: safety (detection and reaction to obstacles) and more control options for chaired people, including controlling the operation of nearby appliances and doors. Another point for the future work is to employee more subjects to investigate the performance of the proposed system before deploying it in real-life scenarios. This may help to avoid real-time problems. In addition, a comparison between different modes in terms of computational time will be conducted to show how the proposed model is fast enough for real applications. Moreover, different environments with different numbers of obstacles will be used to investigate the robustness of the proposed system against real environments. It is also worth mentioning that the joystick can be used instead of designing a four-button pad for manual control.

Acknowledgments: The members of the Electronics and Communication Engineering Department, Suez Canal University, Ismailia, Egypt, are acknowledged for their assistance in prototype preparation and their helpful comments.

Bibliography

- G. Al-Hudhud, Affective command-based control system integrating brain signals in commands control systems, J. Comput. Hum. Behav. 30 (2014), 535–541.
- [2] J. B. Anderson, *Digital transmission engineering*, 12th ed., John Wiley & Sons, USA, 2006.
- [3] R. Anderson and D. Cervo, Pro Arduino (technology in action), 1st ed., Springer, USA, 2013.
- [4] M. Banzi and M. Shiloh, Getting started with arduino, 1st ed., O'Reilly Media, Inc., USA, 2009.
- [5] T. F. Bastos-Filho, F. A. Cheein, S. M. Torres Muller, W. Cardoso Celeste, C. de la Cruz, D. Cruz Cavalieri, M. Sarcinelli-Filho, P. F. Santos Amaral, E. Perez, C. M. Soria and R. Carelli, Towards a new modality-independent interface for a robotic wheelchair, *IEEE Trans. Neural Syst. Rehab Eng.* 22 (2014), 567–584.
- [6] J. Bayle, C Programming for arduino, 1st ed., Packt Publishing Ltd., UK, 2013.
- [7] L. M. Bergasa, M. Mazo, A. Gardel, J. C. Garca, A. E. M. A. Ortuno and A. E. Mendez, Guidance of a wheelchair for handicapped people by face tracking, in: *Proceedings of the 7th IEEE International Conference on Emerging Technologies and Factory Automation (ETFA'99)*, vol. 1, pp. 105–111, IEEE, 1999.
- [8] L. M. Bergasa, M. Mazo, A. Gardel, R. Barea and L. Boquete, Commands generation by face movements applied to the guidance of a wheelchair for handicapped people, in: *Proceedings of the 15th International Conference on Pattern Recognition*, vol. 4, pp. 660–663, IEEE, 2000.
- [9] T. Carlson, R. Leeb, R. Chavarriaga and J. del R. Millan, The birth of the brain-controlled wheelchair, in: *IEEE/RSJ International Conference on Intelligent Robots and Systems (IROS)*, pp. 5444–5445, IEEE, 2012.
- [10] F. Carrino, J. Tscherrig, E. Mugellini, O. Abou Khaled and R. Ingold, Head-computer interface: a multimodal approach to navigate through real and virtual worlds, in: *Proceedings of 14th International Conference of Human-Computer Interaction* (HCI), Interaction Techniques and Environments, vol. 6762, pp. 222–230, Springer, Orlando, FL, USA, 2011.
- [11] B. Dicianno, D. M. Spaeth, R. A. Cooper, S. G. Fitzgerald and M. Boninger, Advancements in power wheelchair joystick technology: effects of isometric joysticks and signal conditioning on driving performance, *Am. J. Phys. Med. Rehab.* 85 (2006), 250.
- [12] A. D'Ausilio, Arduino: a low-cost multipurpose lab equipment, J. Behav. Res. Methods 44 (2012), 305–313.
- [13] J. Fan, S. Jia, X. Li, W. Lu, J. Sheng, L. Gao and J. Yan, Motion control of intelligent wheelchair based on sitting postures, in: International Conference on Mechatronics and Automation (ICMA), pp. 301–306, IEEE, 2011.

- [14] P. M. Faria, R. A. M. Braga, E. Valgode and L. P. Reis, Interface framework to drive an intelligent wheelchair using facial expressions, in: *IEEE International Symposium on Industrial Electronics (ISIE)*, pp. 1791–1796, IEEE, 2007.
- [15] B. M. Faria, L. Ferreira, L. P. Reis, N. Lau, M. Petry and J. Couto, Manual control for driving an intelligent wheelchair: a comparative study of joystick mapping methods, *Environment* **17** (2012), 18.
- [16] B. M. Faria, S. Vasconcelos, L. P. Reis and N. Lau, Evaluation of distinct input methods of an intelligent wheelchair in simulated and real environments: a performance and usability study, J. Assist. Technol. 25 (2013), 88–98.
- [17] B. M. Faria, L. M. Ferreira, L. P. Reis, N. Lau and M. Petry, Intelligent wheelchair manual control methods, in: *Portuguese Conference on Artificial Intelligence*, pp. 271–282, Springer, 2013.
- [18] B. M. Faria, L. P. Reis and N. Lau, A survey on intelligent wheelchair prototypes and simulators, in: New Perspectives in Information Systems and Technologies, vol. 1,, pp. 545–557, Springer, 2014.
- [19] B. M. Faria, L. P. Reis and N. Lau, Adapted control methods for cerebral palsy users of an intelligent wheelchair, J. Intell. Robot. Syst. 77 (2014), 299–312.
- [20] P. S. Gajwani and S. A. Chhabria, Eye motion tracking for wheelchair control, Int. J. Inf. Technol. 2 (2010), 185-187.
- [21] J. Gomez-Gil, I. San-Jose-Gonzalez, L. F. Nicolas-Alonso and S. Alonso-Garcia, <u>Steering a tractor by means of an EMG-based</u> human-machine interface, *J. Sensors* **11** (2011), 7110–7126.
- [22] P. Jia, H. H. Hu, T. Lu and K. Yuan, Head gesture recognition for hands-free control of an intelligent wheelchair, *Ind. Robot* **34** (2007), 60–68.
- [23] J.-S. Han, Z. Zenn Bien, D.-J. Kim, H.-E. Lee and J.-S. Kim, Human-machine interface for wheelchair control with EMG and its evaluation, in: Proceedings of the 25th Annual International Conference of the IEEE Engineering in Medicine and Biology Society, vol. 2, pp. 1602–1605, IEEE, 2003.
- [24] U. Hess, P. Philippot and S. Blairy, Facial reactions to emotional facial expressions: affect or cognition?, *Cognit. Emotion* **12** (1998), 509–531.
- [25] D. Huang, K. Qian, D.-Y. Fei, W. Jia, X. Chen and O. Bai, Electroencephalography (EEG)-based brain-computer interface (BCI): a 2-D virtual wheelchair control based on event-related desynchronization/synchronization and state control, *IEEE Trans. Neural Syst. Rehab. Eng.* **20** (2012), 379–388.
- [26] X. Huo and M. Ghovanloo, Using unconstrained tongue motion as an alternative control mechanism for wheeled mobility, IEEE Trans. Biomed. Eng. 56 (2009), 1719–1726.
- [27] X. Huo, H. Park, J. Kim and M. Ghovanloo, A dual-mode human computer interface combining speech and tongue motion for people with severe disabilities, *IEEE Trans. Neural Syst. Rehab. Eng.* **21** (2013), 979–991.
- [28] A. Ismail and A. Vigneron, A new trajectory similarity measure for GPS data, in: *Proceedings of the 6th ACM SIGSPATIAL International Workshop on GeoStreaming*, pp. 19–22, ACM, 2015.
- [29] I. Iturrate, J. Antelis and J. Minguez, Synchronous EEG brain-actuated wheelchair with automated navigation, in: *IEEE International Conference on Robotics and Automation (ICRA'09)*, pp. 2318–2325, IEEE, 2009.
- [30] J. S. Ju, Y. Shin and E. Y. Kim, Intelligent wheelchair (IW) interface using face and mouth recognition, in: *Proceedings of the* 14th international conference on Intelligent user interfaces, pp. 307–314, ACM, 2009.
- [31] J. Kim, H. Park, J. Bruce, E. Sutton, D. Rowles, D. Pucci, J. Holbrook, J. Minocha, B. Nardone, D. West, A. Laumann, E. Roth, M. Jones, E. Veledar and M. Ghovanloo, The tongue enables computer and wheelchair control for people with spinal cord injury, J. Sci. Transl. Med. 5 (2013), 213ra166.
- [32] J. Kittler and F. M. Alkoot, Sum versus vote fusion in multiple classifier systems, *IEEE Trans. Pattern Anal. Mach. Intell.* 25 (2003), 110–115.
- [33] L. I. Kuncheva, A theoretical study on six classifier fusion strategies, *IEEE Trans. Pattern Anal. Mach. Intell.* 24 (2002), 281–286.
- [34] Y. Kuno, N. Shimada and Y. Shirai, Look where you're going[robotic wheelchair], *IEEE Robot. Automat. Mag.* 10 (2003), 26–34.
- [35] C.-S. Lin, C. Ho, W. Chen, C. Chiu and M. Yeh, Powered wheelchair controlled by eye-tracking system, *Opt. Appl.* **36** (2006), 401.
- [36] J.-S. Lin, K.-C. Chen and W.-C. Yang, EEG and eye-blinking signals through a brain-computer interface based control for electric wheelchairs with wireless scheme, in: 4th International Conference on New Trends in Information Science and Service Science (NISS), pp. 731–734, IEEE, 2010.
- [37] B.-U. Meyer, K. Werhahn, J. C. Rothwell, S. Roericht and C. Fauth, Functional organisation of corticonuclear pathways to motoneurones of lower facial muscles in man, *Exp. Brain Res.* **101** (1994), 465–472.
- [38] I. Moon, M. Lee, J. Chu and M. Mun, Wearable EMG-based HCI for electric-powered wheelchair users with motor disabilities, in: *Proceedings of the 2005 IEEE International Conference on Robotics and Automation (ICRA)*, pp. 2649–2654, IEEE, 2005.
- [39] M. Njah and M. Jallouli, Fuzzy-ekf controller for intelligent wheelchair navigation, J. Intell. Syst. 25 (2016), 107–121.
- [40] S. P. Parikh, V. Grassi, V. Kumar and J. Okamoto, Integrating human inputs with autonomous behaviors on an intelligent wheelchair platform, *IEEE J. Intell. Syst.* 22 (2007), 33–41.
- [41] B. Rebsamen, E. Burdet, C. Guan, H. Zhang, C. L. Teo, Q. Zeng, C. Laugier and M. H. Ang Jr, Controlling a wheelchair indoors using thought, *IEEE Intell. Syst.* 22 (2007), 18–24.
- [42] E.-J. Rechy-Ramirez, H. Hu and K. McDonald-Maier, Head movements based control of an intelligent wheelchair in an indoor environment, in: *IEEE International Conference on Robotics and Biomimetics (ROBIO)*, pp. 1464–1469, IEEE, 2012.
- [43] A. Ross and A. Jain, Information fusion in biometrics, *Pattern Recognit. Lett.* 24 (2003), 2115–2125.

- [44] N. A. Semary, A. Tharwat, E. Elhariri and A. E. Hassanien, Fruit-based tomato grading system using features fusion and support vector machine, in: *Intelligent Systems' 2014*, pp. 401–410, Springer, 2015.
- [45] M. K. Shahin, A. M. Badawi and M. E. Rasmy, A multimodal hand vein, hand geometry, and fingerprint prototype design for high security biometrics, in: *International Biomedical Engineering Conference (CIBEC)*, pp. 1–6, IEEE, 2008.
- [46] M. M. Sharif, A. Tharwat, A. E. Hassanien, H. A. Hefny and G. Schaefer, Enzyme function classification based on Borda count ranking aggregation method, in: *Machine Intelligence and Big Data in Industry*, pp. 75–85, Springer, 2016.
- [47] S. K. Swee and L. Z. You, Fast Fourier analysis and EEG classification brainwave controlled wheelchair, in: 2nd International Conference on Control Science and Systems Engineering (ICCSSE), pp. 20–23, IEEE, 2016.
- [48] H. Tamura, T. Murata, Y. Yamashita, K. Tanno and Y. Fuse, Development of the electric wheelchair hands-free semi-automatic control system using the surface-electromyogram of facial muscles, J. Artif. Life Robot. 17 (2012), 300–305.
- [49] A. Tharwat, A. F. Ibrahim and H. A. Ali, Multimodal biometric authentication algorithm using ear and finger knuckle images, in: *Seventh International Conference on Computer Engineering & Systems (ICCES)*, pp. 176–179, IEEE, 2012.
- [50] A. Tharwat, M. M. Sharif, A. E. Hassanien and H. A. Hefeny, Improving enzyme function classification performance based on score fusion method, in: *International Conference on Hybrid Artificial Intelligence Systems*, pp. 530–542, Springer, 2015.
- [51] A. Tharwat, T. Gaber and A. E. Hassanien, Two biometric approaches for cattle identification based on features and classifiers fusion, *Int. J. Image Mining* 1 (2015), 342–365.
- [52] A. Thobbi, R. Kadam and W. Sheng, Achieving remote presence using a humanoid robot controlled by a non-invasive BCI device, Int. J. Artif. Intell. Mach. Learn. 10 (2010), 41–45.
- [53] R. Valenti, N. Sebe and T. Gevers, Combining head pose and eye location information for gaze estimation, IEEE Trans. Image Process. 21 (2012), 802–815.
- [54] F. Velasco-Álvarez, A. Fernández-Rodrguez and R. Ron-Angevin, Switch mode to control a wheelchair through EEG signals, in: *Converging Clinical and Engineering Research on Neurorehabilitation II*, pp. 801–805, Springer, 2017.
- [55] P. Viswanathana, J. L. Bella, R. H. Wanga, B. Adhikarib, A. K. Mackworthb, A. Mihailidisa, W. C. Millerc and I. M. Mitchellb, A Wizard-of-Oz intelligent wheelchair study with cognitively-impaired older adults: attitudes toward user control, in: *IEEE/ RSJ International Conference on Intelligent Robots and Systems (IROS) Workshop on Assistive Robotics for Individuals with Disabilities: HRI Issues and Beyond*, pp. 1–4, 2014.
- [56] L. Wei, H. Hu, T. Lu and K. Yuan, Evaluating the performance of a face movement based wheelchair control interface in an indoor environment, in: *IEEE International Conference on Robotics and Biomimetics (ROBIO)*, pp. 387–392, IEEE, 2010.
- [57] X. Xu, Y. Zhang, Y. Luo and D. Chen, Robust bio-signal based control of an intelligent wheelchair, J. Robot. 2 (2013), 187–197.
- [58] Y. Yasui, A brainwave signal measurement and data processing technique for daily life applications, J. Physiol. Anthropol. 28 (2009), 145–150.
- [59] G. Zimmermann and G. Vanderheiden, The universal control hub: an open platform for remote user interfaces in the digital home, in: 12th International Conference, Human-Computer Interaction (HCI), Interaction Platforms and Techniques, vol. 4551, pp. 1040–1049, Springer, Beijing, China, 2007.